

# CPT7

Compact dual antenna enclosure with SPAN GNSS+INS technology delivers 3D position, velocity and attitude



## World-leading GNSS+INS technology

SPAN GNSS+INS technology brings together two different but complementary technologies: Global Navigation Satellite System (GNSS) positioning and Inertial Navigation System (INS). The absolute accuracy of GNSS positioning and the stability of Inertial Measurement Unit (IMU) gyro and accelerometer measurements are deeply coupled to provide an exceptional 3D navigation solution that is stable and continuously available, even through periods when satellite signals are blocked.

## CPT7 overview

The CPT7 is a compact, single enclosure GNSS+INS receiver powered by world class OEM7 technology from Hexagon | NovAtel. Capable of delivering up to centimeter-level accuracy, customers can choose from a variety of positioning modes to ensure they have the optimal level of accuracy for their application.

The CPT7 contains a high performing and highly reliable Honeywell HG4930 Micro Electromechanical System (MEMS) IMU to deliver leading-edge SPAN technology from NovAtel in an integrated single enclosure solution. It provides tactical grade performance for unmanned vehicles, mobile mapping and other commercial and/or military guidance applications. The CPT7 is a small, lightweight and low-power solution with multiple communication interfaces for easy integration on multiple platforms.

## CPT7 advantages

The deep coupling of the GNSS and IMU measurements delivers the most satellite observations and the most accurate, continuous solution possible. Further, the CPT7 is comprised entirely of commercial components, simplifying export restrictions involved with traditional GNSS+INS systems.

## Improve CPT7 accuracy

CPT7 provides your choice of accuracy and performance, from decimeter to RTK-level positioning. For more demanding applications, Inertial Explorer post-processing software can be used to post-process the real-time SPAN GNSS+INS solution to provide the system's highest level of accuracy.

## Benefits

- High performance SPAN GNSS+INS solution
- Small, low-power, all-in-one GNSS+INS enclosure
- Easy integration into space and weight constrained applications
- Commercially exportable system
- Rugged design ideal for challenging environments
- Enhanced connection options including serial, USB, CAN and Ethernet
- Future-proof for upcoming GNSS signal support

## Features

- MEMS gyros and accelerometers
- Small size, rugged and lightweight
- Dedicated wheel sensor input
- TerraStar Correction Services supported over multi-channel L-Band and IP connections
- Advanced interference mitigation features
- SPAN GNSS+INS capability with configurable application profiles
- Dual antenna ALIGN heading
- 16 GB of internal storage
- Four receiver status LEDs

**SPAN system performance<sup>1</sup>**

**Signal tracking<sup>2,3</sup>**  
 GPS L1 C/A, L1C, L2C, L2P, L5  
 GLONASS<sup>4</sup> L1 C/A, L2 C/A, L2P, L3, L5  
 Galileo<sup>5</sup> E1, E5 AltBOC, E5a, E5b  
 BeiDou<sup>6</sup> B1I, B1C, B2I, B2a, B2b  
 QZSS L1 C/A, L1C, L2C, L5  
 NavIC (IRNSS) L5  
 SBAS L1, L5  
 L-Band (primary RF only) up to 5 channels

**Horizontal position accuracy (RMS)**  
 Single Point L1 1.5 m  
 Single Point L1/L2 1.2 m  
 SBAS<sup>7</sup> 60 cm  
 DGPS 40 cm  
 TerraStar-L<sup>8</sup> 40 cm  
 TerraStar-C PRO<sup>8</sup> 2.5 cm  
 TerraStar-X<sup>8</sup> 2.0 cm  
 RTK 1 cm + 1 ppm  
 Initialization time < 10 s  
 Initialization reliability > 99.9%

**ALIGN heading accuracy**  
**Baseline Accuracy (RMS)**  
 2 m 0.08 deg  
 4 m 0.05 deg

**Heave performance<sup>9</sup>**  
 Instantaneous Heave 5 cm or 5%  
 Delayed Heave 3.5 cm or 3.5%  
 Post-Processed Heave<sup>10</sup> 2.5 cm or 2.5%

**Maximum data rate**  
 IMU raw data rate 100 Hz or 400 Hz<sup>11</sup>  
 INS solution Up to 200 Hz

**Time to first fix**  
 Cold start<sup>12</sup> < 39 s (typ)  
 Hot start<sup>13</sup> < 20 s (typ)

**Signal reacquisition**  
 L1 < 0.5 s (typ)  
 L2/L5 < 1.0 s (typ)

**Time accuracy<sup>14</sup>** 20 ns RMS

**Velocity accuracy** < 0.03 m/s RMS

**Velocity limit<sup>15</sup>** 515 m/s

**IMU performance<sup>16</sup>**

**Gyroscope performance**  
 Technology MEMS  
 Input rate (max) ±200°/s

**Accelerometer performance**  
 Technology MEMS  
 Range ±20 g

**Physical and Electrical**

**Dimensions<sup>17</sup>** 90 x 60 x 60 mm

**Weight** 500 g

**Power**  
 Power consumption<sup>18</sup> 9 W (typ)  
 Input voltage +9 to +32 VDC

**Antenna LNA power output**  
 Output voltage 5 VDC ±5%  
 Maximum current 200 mA

**Input/Output connectors**  
 Antennas 2 x SMA  
 Power and I/O 2 x Fischer Core  
 16 pin DPBU 104 A086 140G/240G

**Status LEDs**  
 Power  
 Position  
 INS  
 Logging

**Communication ports**  
 RS-422 1  
 RS-232 1  
 USB Device 1  
 Ethernet 1  
 CAN Bus 1  
 Event Input 3  
 Event Output 3  
 Wheel Sensor Input 1

**Environmental**

**Temperature**  
 Operating -40°C to +71°C  
 Storage -40°C to +85°C

**Humidity** 95% non-condensing

**Submersion** 2 m for 12 hours (IEC 60529 IP68)

**Water** MIL-STD-810H, Method 512.6

**Dust** MIL-STD-810H, Method 510.7

**Vibration (operating) Random** MIL-STD-810H, Method 514.8, Category 24, 7.7 g RMS

**Sinusoidal** IEC 60068-2-6

**Acceleration (operating)** MIL-STD-810H, Method 513.8, Procedure II (G Loading - 15 g)

**Bump (operating)** IEC 60068-2-27 Ea (25 g)

**Shock (operating)** MIL-STD-810H, Method 516.8, Procedure 1, 40 g, 11 ms terminal sawtooth

**Compliance** FCC, ISED, CE<sup>19</sup>

- Firmware solutions**
- Field upgradeable firmware and software models
  - Configurable PPS output
  - SPAN Enhanced Profiles
  - ALIGN
  - TerraStar PPP
  - RTK
  - RTK ASSIST
  - API

- Optional accessories**
- Power and I/O cable
  - Mounting Plate
  - VEXXIS series antennas
  - Compact GNSS antennas
  - NovAtel Application Suite
  - GrafNav/GrafNet
  - Inertial Explorer

**Performance During GNSS Outages<sup>21,22</sup>**

Outage Duration	Positioning Mode	Position Accuracy (m) RMS		Velocity Accuracy (m/s) RMS		Attitude Accuracy (Degrees) RMS		
		Horizontal	Vertical	Horizontal	Vertical	Roll	Pitch	Heading
0 s	RTK <sup>20</sup>	0.02	0.03					
	PPP	0.06	0.15	0.015	0.010	0.010	0.010	0.030
	SP	1.00	0.60					
	Post-Processed <sup>10</sup>	0.01	0.02	0.015	0.010	0.003	0.003	0.010
10 s	RTK <sup>20</sup>	0.12	0.08					
	PPP	0.16	0.20	0.035	0.020	0.018	0.018	0.040
	SP	1.10	0.65					
	Post-Processed <sup>10</sup>	0.01	0.02	0.015	0.010	0.003	0.003	0.010
60 s	RTK <sup>20</sup>	3.82	0.73					
	PPP	3.86	0.85	0.165	0.030	0.030	0.030	0.055
	SP	4.80	1.30					
	Post-Processed <sup>10</sup>	0.11	0.05	0.017	0.010	0.004	0.004	0.014

1. Typical SPAN system performance values when using this IMU. Performance specifications subject to GNSS system characteristics, Signal-in-Space (SIS) operational degradation, ionospheric and tropospheric conditions, satellite geometry, baseline length, multipath effects and the presence of intentional or unintentional interference. 2. Model-configurable to track L5/E5a (all / Galileo) through L2 (GPS) or L3/E5b/B2 (GLONASS / Galileo / BeiDou) through L2 (GLONASS). See manual for details. 3. The secondary antenna input does not support L-Band or SBAS signals. 4. Hardware ready for L3 and L5. 5. E1bc support only. 6. Requires an MFD model receiver. 7. GPS-only. 8. Requires subscription to TerraStar data service. Subscriptions available from NovAtel. 9. Requires SPAN Marine Profile. 10. Post-processing results using Waypoint Inertial Explorer. 11. Configurable with appropriate model. 12. Typical value. No almanac or ephemerides and no approximate position or time. 13. Typical value. Almanac and recent ephemerides saved and approximate position and time entered. 14. Time accuracy does not include biases due to RF or antenna delay. 15. Export licensing restricts operation to a maximum of 515 meters per second, message output impacted above 500 m/s. 16. Supplied by IMU manufacturer. 17. Dimensions do not include mounting feet. 18. Typical values using serial port communication without interference mitigation. Consult the OEM7 Installation & Operation User Manual for power supply considerations. 19. Pending. 20. 1 ppm should be added to all position values to account for additional error due to baseline length. 21. Outage statistics were calculated by taking the RMS of the maximum errors over a minimum of 30 complete GNSS outages. Each outage was followed by 120 seconds of full GNSS availability before the next outage was applied. High accuracy GPS updates (fixed ambiguities) were available immediately before and after each outage. The survey data used to generate these statistics had frequent changes in azimuth. 22. Outage performance achieved with one antenna.

Contact Hexagon | NovAtel

sales.nov.ap@hexagon.com 1-800-NOVATEL (U.S. and Canada) or 403-295-4900 | China: 0086-21-68882300 | Europe: 44-1993-848-736 | SE Asia and Australia: 61-400-883-601. For the most recent details of this product: novatel.com

ALIGN, GrafNav/GrafNet, Inertial Explorer, NovAtel, OEM7, PwrPak7, SPAN, TerraStar and VEXXIS are trademarks of NovAtel, Inc., entities within the Hexagon Autonomy & Positioning division, their affiliated entities, and/or their licensors. All other trademarks are properties of their respective owners.

©2020 NovAtel Inc. All rights reserved. NovAtel is part of Hexagon. NovAtel makes no representation or warranty regarding the accuracy of the information in this publication. This document gives only a general description of the product(s) or service(s) offered by NovAtel, and, except where expressly provided otherwise, shall not form part of any contract. Such information, the products and conditions of supply are subject to change without notice.